

Shunt release for NZM2/3, 208-250AC/DC, Push-in terminals



**Part no.** NZM2/3-XA208-250AC/DC-PI  
**189803**  
**EL Number** 4362990  
**(Norway)**

|  |  |
|--|--|
| Product name   | Eaton Moeller series NZM release   |
| Part no.   | NZM2/3-XA208-250AC/DC-PI   |
| EAN  | 4015081877980  |
| Product Length/Depth   | 115 millimetre   |
| Product height   | 65 millimetre  |
| Product width  | 75 millimetre  |
| Product weight   | 0.08 kilogram  |
| Compliances  | UL/CSA<br>IEC<br>RoHS conform  |
| Product Tradename  | NZM  |
| Product Type   | Accessories  |
| Product Sub Type   | Release  |
| Type   | Accessory Shunt release  |
| Special features   | When the shunt release is live, contact with the circuit-breaker's main contacts on switching on is reliably prevented. Shunt release modules cannot be installed simultaneously with early-make contact NZM...-XHIV, undervoltage release NZM...-XU..., or relais modules NZM...-X2A... |
| Frame  | NZM2/3   |
| Suitable for   | Motor safety switch<br>Off-load switch   |
| Used with  | NZM3(-4), N(S)3(-4)<br>NZM2(-4), N(S)2(-4)   |
| Voltage type   | AC   |
| Rated control supply voltage   | 208 - 250 V AC/DC  |
| Rated control supply voltage (Us) at AC, 50 Hz - min                             | 208 V  |
| Rated control supply voltage (Us) at AC, 50 Hz - max                             | 250 V  |
| Rated control supply voltage (Us) at AC, 60 Hz - min                             | 208 V  |
| Rated control supply voltage (Us) at AC, 60 Hz - max                             | 250 V  |
| Rated control supply voltage (Us) at DC - min                                    | 208 V  |
| Rated control supply voltage (Us) at DC - max                                    | 250 V  |
| Electric connection type   | Screw connection   |
| Number of contacts (change-over contacts)  | 0  |
| Number of contacts (normally closed contacts)                                    | 0  |
| Number of contacts (normally open contacts)                                      | 0  |
| Connection type  | With push in terminal  |
| Special features   | When the shunt release is live, contact with the circuit-breaker's main contacts on switching on is reliably prevented. Shunt release modules cannot be installed simultaneously with early-make contact NZM...-XHIV, undervoltage release NZM...-XU..., or relais modules NZM...-X2A... |
| 10.2.2 Corrosion resistance  | Meets the product standard's requirements.   |
| 10.2.3.1 Verification of thermal stability of enclosures                         | Meets the product standard's requirements.   |
| 10.2.3.2 Verification of resistance of insulating materials to normal heat       | Meets the product standard's requirements.   |
| 10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects | Meets the product standard's requirements.   |
| 10.2.4 Resistance to ultra-violet (UV) radiation                                 | Meets the product standard's requirements.   |
| 10.2.5 Lifting   | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.2.6 Mechanical impact   | Does not apply, since the entire switchgear needs to be evaluated.   |

|  |  |  |
|--|--|--|
| 10.2.7 Inscriptions                                      |  | Meets the product standard's requirements.   |
| 10.3 Degree of protection of assemblies                  |  | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.4 Clearances and creepage distances                   |  | Meets the product standard's requirements.   |
| 10.5 Protection against electric shock                   |  | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.6 Incorporation of switching devices and components   |  | Does not apply, since the entire switchgear needs to be evaluated.   |
| 10.7 Internal electrical circuits and connections        |  | Is the panel builder's responsibility.   |
| 10.8 Connections for external conductors                 |  | Is the panel builder's responsibility.   |
| 10.9.2 Power-frequency electric strength                 |  | Is the panel builder's responsibility.   |
| 10.9.3 Impulse withstand voltage                         |  | Is the panel builder's responsibility.   |
| 10.9.4 Testing of enclosures made of insulating material |  | Is the panel builder's responsibility.   |
| 10.10 Temperature rise                                   |  | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 Short-circuit rating                               |  | Is the panel builder's responsibility. The specifications for the switchgear must be observed.                                   |
| 10.12 Electromagnetic compatibility                      |  | Is the panel builder's responsibility. The specifications for the switchgear must be observed.                                   |
| 10.13 Mechanical function                                |  | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.                         |

## Technical data ETIM 8.0

|   |   |                  |
|---|---|------------------|
| Low-voltage industrial components (EG000017) / Shunt release (for power circuit breaker) (EC001023)   |   |                  |
| Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Full load current trip (ecl@ss10.0.1-27-37-04-18 [AKF016013]) |   |                  |
| Rated control supply voltage Us at AC 50HZ  | V | 208 - 250        |
| Rated control supply voltage Us at AC 60HZ  | V | 208 - 250        |
| Rated control supply voltage Us at DC   | V | 208 - 250        |
| Voltage type for actuating  |   | AC               |
| Initial value of the undelayed short-circuit release - setting range  | A | 0                |
| End value adjustment range undelayed short-circuit release  | A | 0                |
| Type of electric connection   |   | Screw connection |
| Number of contacts as normally open contact   |   | 0                |
| Number of contacts as normally closed contact   |   | 0                |
| Number of contacts as change-over contact   |   | 0                |
| Suitable for power circuit breaker  |   | No               |
| Suitable for off-load switch  |   | Yes              |
| Suitable for motor safety switch  |   | Yes              |
| Suitable for overload relay   |   | No               |