

## INSTALLATION INFORMATION

PLEASE READ PRIOR TO INSTALLATION



## LEDD125 Series

VISUAL SIGNALLING DEVICE



- EN Translations & Documentation, scan QR Code  
FR Traductions & Documentation, scannez le QR Code  
DE Übersetzungen & Dokumentation, QR-Code scannen  
IT Traduzioni & Documentazione, scansionare il QR code  
ES Traducciones & Documentación, escanear QR code

### APPROVALS AND CONFORMITIES



## General Installation Notes

- Installation must be carried out in accordance with the latest codes and regulations by a qualified electrician.
- Ensure power is disconnected prior to installation or maintenance to avoid danger of electrical shock.
- Environmental exposure conditions during installation should be dry. Moist or wet conditions should be avoided.
- The Lens of the product is Polycarbonate plastic. Do not clean with petroleum-based cleaners.
- For all installations, mount the Beacon ensuring the Lens is above the Base. Any other mounting positions will impair the IP Rating (Ingress Protection) of the Beacon.
- Avoid mounting the Beacon where it will be subjected to excessive vibration.
- The DC supply must be fully rectified and smoothed. If not, suppression will be required. Typical suppression units include: RS 219-2921 or RS 240-696. Both will suffice.

## Installation Instructions

Unscrew the three M3 screws that secure the Base Plate to the Base and gently remove the Base Plate away from the Base.

Pierce the Cable Grommet located in the Base Plate and insert power cable or control cables through the Grommet, pulling the cable back slightly (around 10mm) to allow the Grommet to form a weatherproof seal.

**See Diagram 1** below for a sample method for feeding cables through the Grommet and PCB for final termination into the three-way Terminal Block.




Diagram 1

Once cable length has been set, connect power to the terminals marked 4, 5 & 6 on the three-way Terminal Block located on the PCB (**See Wiring Diagram 1 & 2**)

The flash output required must now be set using the 4 Way DIP Switch located on the PCB. To gain access to the Switch, you will need to remove the Lens from the Base by unscrewing the two M4 screws that hold the Lens in place.

The table below denotes the switch positions required to change the Flash Rate.

Flash Type	FPM (Flashes Per Minute)	Switch Position	
Standard Flash	60	3 = ON	4 = OFF
Double Flash	130	3 = OFF	4 = ON
Rapid Flash	190	3 = ON	4 = ON
Static Mode	No Flash	3 = OFF	4 = OFF
LED Output	N/A	2 = OFF - Flashing LED's 2 = ON - Constant LED's	


The LEDD125 Series is supplied pre-set to Standard Flash (Switch Position 3 ON, all other positions OFF)

Once the Flash Rate required has been set, locate the Base Plate back onto the Base using the three M3 screws removed earlier.


Now secure the Base to an appropriate surface using the 3 x 4.5mm fixing holes located on the Base with 4mm screws (not supplied).

Lastly, secure the Lens back onto the Base using the two M4 screws removed earlier, ensuring the Base 'O' Ring is in place.

### Wiring Diagram



Wiring Diagram 1 (DC)



Wiring Diagram 2 (AC)

Moflash Signalling Limited accepts no liability for any consequences following use of this document. Any technical specifications and products referred to within this document are subject to change without notice due to continual improvement and product development policies. All dB(A) figures are subject to environmental conditions. The units are sold under Moflash standard conditions of sale, available on request. Additional resources, including installation sheet translations, certificates and DoCs are available from the [www.moflash.co.uk](http://www.moflash.co.uk) website.