




			6 00
Product designation			MINIATURE RELAYS
Product type designation			HR302C
Contact characteristics			
Contact configuration			2 C/O
Rated insulation voltage Ui IEC/EN		V	250
Rated impulse withstand voltage Uimp		kV	6
IEC Conventional free air thermal current Ith		Α	8
Maximum instantaneous current		Α	20
Rated current (In)		Α	8
Relay control voltage		V	24VDC
Max contrallable power in			
	AC-1	W	2000
	AC-15	VA	150
Rated operating power AC-1			
		VA	2000
Rated operating power AC-15			
	230 VAC	VA	150
Single-phase motor control			
5 1	230VAC	kW	0.2
Rated operating current DC-1			
· · · · · · · · · · · · · · · · · · ·	30V	Α	8
	110V	Α	0.3
	220V	Α	0.1
Minimum switching load		V / mA	5 / 100
Contact impedance		mΩ	100
Contact material			AgSnO2
Operating times			7 tg61162
Closing		ms	10
Opening		ms	5
Operations		1110	
Mechanical life		cycles	10000000
Electrical life AC1		cycles	50000
Coil characteristics		Cycles	30000
Average coil consumption AC at 20°C		VA	0.9
Average coil consumption DC at 20°C		W	0.45
Operating range		v v	0.70
	Closing	% Un	75110
	Opening		1030
Maximum avala fraguanav	Opening	% Un cycles/h	
Maximum cycle frequency Mechanical features		cycles/n	3000
		Nim	0.6
Max socket terminal tightening torque		Nm	0.6
Socket screw tightening tool (cross / flat blade) Conductor section			PH1 / 4.5mm


AWG/Kcmil




		min		20
		max		14
	IEC			
		min	mm²	0.5
		max	mm²	2.5
Operating position				
		normal		Any
Fixing				On 35mm DIN rail and with screw
Ambient conditions				
Temperature				
•	Operating temperature			
		min	°C	-40
		max	°C	+85
	Storage temperature			_
		min	°C	-40
		max	°C	+85
Other features				
Indication				No
Mechanical contact po	sition indicator			No
Mechanical test actuate	or			No
Dimensions				







Wiring diagrams



Certifications and compliance

Compliance

IEC/EN 61810

Certificates

CSA

cURus

EAC





MINIATURE RELAY, 24VDC, 8A, 2C/O CONTACT. FITTING ON SOCKET HR5XS2...

۱/	ח	F
v	\boldsymbol{L}	ᆫ

ETIM classification

ETIM 8.0 EC001437 - Switching relay