

Product Environmental Profile

9-Port GBIT Switch 8-Port PoE 92W




General information

Representative product	9-Port GBIT Switch 8-Port PoE 92W - R9H9SWP92
Description of the product	This PoE Ethernet switch is to provide data transmission between each switch port. It also provides power to the PoE WAPs connected to switch PoE enabled ports.
Functional unit	To transmit Ethernet LAN data and 48V DC PoE power over a distance of 100m during 5 years at 100% use rate and for single port, the maximum PoE power level is about 30W and for the maximum PoE power level for whole switch is about 92W in accordance with the standard IEC 60950-1

Constituent materials

Reference product mass 2095 g including the product, its packaging



Plastics	9.2%
Metals	44.7%
Others	46.1%

Substance assessment

Products of this range are designed in conformity with the requirements of the RoHS directive (European Directive 2011/65/EU of 2 January 2013, amended in March 2015, 2015/863/EU and in November 2017, 2017/2102/EU) and do not contain, or only contain in the authorised proportions, lead, mercury, cadmium, hexavalent chromium or flame retardants (polybrominated biphenyls - PBB, polybrominated diphenyl ethers – PBDE), Bis (2-ethylhexyl)phthalate - DEHP, Benzyl butyl phthalate– BBP, Dibutyl phthalate - DBP, Diisobutyl phthalate - DIBP) as mentioned in the Directive.

Details of ROHS and REACH substances information are available on the Schneider-Electric Green Premium website

<http://www2.schneider-electric.com/sites/corporate/en/products-services/green-premium/green-premium.page>

Additional environmental information

The 9-Port GBit Switch 8-Port PoE 92W presents the following relevant environmental aspects


Manufacturing	Manufactured at a production site complying with the regulations
Distribution	Weight and volume of the packaging optimized, based on the European Union's packaging directive Packaging weight is 360.9 g, consisting of Cardboard (92.75%) , Paper (7%) & Wood(0.25%) Product distribution optimised by setting up local distribution centres
Installation	This product does not require special installation operation. The disposal of the packaging materials are accounted for during the installation phase (including transport to disposal).
Use	The product does not require special maintenance operations.
End of life	End of life optimized to decrease the amount of waste and allow recovery of the product components and materials This product contains PCBA for Power adaptor (55.4g) & PCBA for GBit Ethernet switch (141.6g) & Cables (190g) that should be separated from the stream of waste so as to optimize end-of-life treatment. The location of these components and other recommendations are given in the End of Life Instruction document which is available on the Schneider-Electric Green Premium website http://www2.schneider-electric.com/sites/corporate/en/products-services/green-premium/green-premium.page Recyclability potential: 54% Based on "ECO'DEEE recyclability and recoverability calculation method" (version V1, 20 Sep. 2008 presented to the French Agency for Environment and Energy Management: ADEME).

Environmental impacts

Reference life time	10 years			
Product category	Copper telecom accessory			
Installation elements	End of life of the packaging, materials for installation			
Use scenario	The product is in active mode 90% of the time with a power use of 102W and in Standby mode 10% of the time with a power use of 3.06W, for 10 years			
Geographical representativeness	France			
Technological representativeness	The Modules of Technologies such as material production, manufacturing process and transport technology used in this PEP analysis (LCA-EIME in this case) are Similar and representative of the actual type of technologies used to make the product in production.			
Energy model used	Manufacturing	Installation	Use	End of life
	Manufacturing Plant Location: China	Electricity mix; AC; consumption mix, at consumer; 230V; FR	Electricity mix; AC; consumption mix, at consumer; 230V; FR	Electricity mix; AC; consumption mix, at consumer; 230V; FR

Compulsory indicators		9-Port GBit Switch 8-Port PoE 92W - R9H9SWP92					
Impact indicators	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Contribution to mineral resources depletion	kg Sb eq	2.68E-03	2.41E-03	0*	0*	2.71E-04	0*
Contribution to the soil and water acidification	kg SO ₂ eq	1.12E+00	5.52E-02	1.10E-03	0*	1.06E+00	6.85E-04
Contribution to water eutrophication	kg PO ₄ ³⁻ eq	3.64E-01	7.03E-02	2.52E-04	0*	2.93E-01	2.41E-04
Contribution to global warming	kg CO ₂ eq	9.44E+02	2.12E+01	2.42E-01	0*	9.22E+02	6.43E-01
Contribution to ozone layer depletion	kg CFC11 eq	7.30E-05	3.49E-06	0*	0*	6.95E-05	2.72E-08
Contribution to photochemical oxidation	kg C ₂ H ₄ eq	1.19E-01	5.01E-03	7.86E-05	0*	1.14E-01	6.91E-05

Resources use	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Net use of freshwater	m3	2.34E+01	6.02E+00	0*	0*	1.74E+01	0*
Total Primary Energy	MJ	1.18E+05	3.89E+02	0*	0*	1.17E+05	0*



Optional indicators	9-Port GBIT Switch 8-Port PoE 92W - R9H9SWP92						
Impact indicators	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Contribution to fossil resources depletion	MJ	1.29E+04	2.03E+02	3.40E+00	0*	1.27E+04	2.67E+00
Contribution to air pollution	m³	7.10E+04	2.30E+03	1.05E+01	0*	6.87E+04	2.43E+01
Contribution to water pollution	m³	5.27E+04	1.94E+03	3.97E+01	0*	5.05E+04	2.35E+02
Resources use	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Use of secondary material	kg	5.51E-01	5.51E-01	0*	0*	0*	0*
Total use of renewable primary energy resources	MJ	2.87E+01	1.08E+01	4.55E-03	0*	1.79E+01	3.36E-03
Total use of non-renewable primary energy resources	MJ	1.18E+05	3.79E+02	0*	0*	1.17E+05	0*
Use of renewable primary energy excluding renewable primary energy used as raw material	MJ	2.81E+01	1.01E+01	4.55E-03	0*	1.79E+01	3.36E-03
Use of renewable primary energy resources used as raw material	MJ	6.38E-01	6.38E-01	0*	0*	0*	0*
Use of non renewable primary energy excluding non renewable primary energy used as raw material	MJ	1.18E+05	3.66E+02	0*	0*	1.17E+05	0*
Use of non renewable primary energy resources used as raw material	MJ	1.23E+01	1.23E+01	0*	0*	0*	0*
Use of non renewable secondary fuels	MJ	0.00E+00	0*	0*	0*	0*	0*
Use of renewable secondary fuels	MJ	0.00E+00	0*	0*	0*	0*	0*
Waste categories	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Hazardous waste disposed	kg	1.36E+03	6.54E+00	0*	0*	1.35E+03	2.92E+00
Non hazardous waste disposed	kg	9.48E+01	6.03E+00	0*	0*	8.88E+01	1.03E-02
Radioactive waste disposed	kg	9.31E-01	9.95E-03	0*	0*	9.21E-01	0*
Other environmental information	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Materials for recycling	kg	1.42E+00	1.22E-01	0*	3.58E-01	0*	9.42E-01
Components for reuse	kg	0.00E+00	0*	0*	0*	0*	0*
Materials for energy recovery	kg	9.56E-02	0*	0*	0*	0*	9.56E-02
Exported Energy	MJ	2.28E-03	2.14E-04	0*	2.07E-03	0*	0*

* represents less than 0.01% of the total life cycle of the reference flow

Life cycle assessment performed with EIME version 5.9.3, database version 2016-11 in compliance with ISO14044.

The use phase is the life cycle phase which has the greatest impact on the majority of environmental indicators except Abiotic depletion (elements, ultimate reserves) (ADPe for EN15804) (based on compulsory indicators).

Please note that the values given above are only valid within the context specified and cannot be used directly to draw up the environmental assessment of an installation.

Registration number	ENVPEP2203016_V1	Drafting rules	PCR-ed3-EN-2015 04 02
Date of issue	04/2022	Supplemented by	PSR-0005-ed2-EN-2016 03 29
Validity period	5 years	Information and reference documents	www.pep-ecopassport.org
<i>Independent verification of the declaration and data</i>			
Internal	X	External	
<i>The elements of the present PEP cannot be compared with elements from another program.</i>			
<i>Document in compliance with ISO 14021:2016 « Environmental labels and declarations - Self-declared environmental claims (Type II environmental labelling) »</i>			

Schneider Electric Industries SAS
Country Customer Care Center
<http://www.schneider-electric.com/contact>
35, rue Joseph Monier
CS 30323
F- 92506 Rueil Malmaison Cedex
RCS Nanterre 954 503 439
Capital social 896 313 776 €

www.schneider-electric.com

ENVPEP2203016_V1

Published by Schneider Electric

© 2019 - Schneider Electric – All rights reserved

04/2022