
PRODUCT-DETAILS

PSTX105-600-70

PSTX105-600-70 Softstarter - 105 A - 208 ... 600 V AC



Informations générales

Alias commercial mondial	PSTX105-600-70
Extension du type de produit	PSTX105-600-70
Code de produit	1SFA898109R7000
ABB désignation de type	PSTX105-600-70
EAN	7320500501313
Description courte	PSTX105-600-70 Softstarter - 105 A - 208 ... 600 V AC

Description longue

The softstarter PSTX105-600-70 has a rated maximum operational current of 105 A with an operating voltage span from 208...600 V AC. The rated control voltage is between 100...250 V AC at 50/60 Hz. PSTX features a three-phase control soft start and stop through a voltage or a torque ramp. It has built-in bypass for easy installation and energy saving. A RUN, TOR and Event signal is available from relay outputs in NO (normally open state). The PSTX has functions such as current limit, kickstart, analog output, EOL, motor heating and pump cleaning. PSTX also features jog, braking, stand-still brake, diagnostics, sequence start and emergency/fire pump mode as standard. To interact with PSTX, it has a detachable full graphic display with IP66 and 4x outdoor rating. There are four ways to communicate with PSTX. It can be done by hardwire inputs Start/Stop/Reset of fault, and by three programmable digital inputs. Another popular option is the built-in Fieldbus communication Modbus RTU and incl optional ANYBUS modules with every major protocol such as for example Profinet, Profibus, Modbus TCP, Ethernet IP and others. Another way to communicate with PSTX is to use an external adaptor and a Fieldbus plug. PSTX is the complete alternative for any motor starting application. It's suitable for medium to large-sized three-phase motors with nominal currents from 30...1250 A inline connection or 52...2160 A inside delta connection. Typical applications are, for example, pumps, fans, compressors, and conveyors.

Commande

Quantité minimum	1 pièce
Code douanier	85371091

Downloads Préférés

Fiche produit, informations techniques	1SFC132012C0201
Instructions et manuels	1SFC132081M0201
CAD Dimensional Drawing	2CDC001079B0201
Wiring Diagram	N/A

Dimensions

Produit Largeur Net	150 mm
Produit Hauteur Net	314 mm
Produit Longueur Net	198 mm
Poids net	4.7 kg

Technique

Tension	208 ... 600 V AC
Rated Control Supply Voltage (U_s)	100 ... 250 V AC
Rated Control Circuit Voltage (U_c)	24 V DC
Fréquence assignée (f)	50/60 Hz Circuit principal 50 / 60 Hz
Rated Operational Power - In-Line Connection (Pe)	(230 V) 30 kW (400 V) 55 kW (500 V) 75 kW
Courant nominal de fonctionnement-- Raccordement en ligne (le)	105 A
Rated Operational Power - Inside Delta Connection	at 230 V 55 kW at 400 V 90 kW at 500 V 110 kW
Rated Operational Current - Inside Delta Connection	181 A
Pourcentage Facteur de service	100 %
Overload Protection	Built-in electronic overload protection
Integrated Electronic Overload	Yes
Adjustable Rated Motor Current le	30 ... 100 %
Starting Capacity at Maximum Rated Current	4xle for 10s

le	
Ramp Time	1 ... 120 second [unit of time]
Initial Voltage During Start	10 ... 99 %
Step Down Voltage	100 ... 10 %
Special Ramp	
Current Limit Function	1.5 ... 7.5 xle
Switch for Inside Delta Connection	Oui
Run Signal Relay	Oui
By-pass Signal Relay	Yes
Fault Signal Relay	Yes
Overload Signal Relay	Oui
Sorties analogiques	0...10 V, 0...20 mA, 4...20 mA
Signal Indication Ready to Start/Standy ON (LED)	Green
Voyant de signal indiquant R (LED)	Green
Signal Indication Protection (LED)	Yellow
Signal Indication Fault (LED)	Red
Communication	Modbus-RTU; Modbus-TCP; Ethernet-IP; EtherCAT; DeviceNet; CANopen; Profibus; Profinet; BACnet-IP; BACnet-MSTP
Indice de protection	IP00
Type de borne	Cable Clamp
Connecting Capacity Main Circuit	Hole Diameter 8.5 mm
Connecting Capacity Control Circuit	Rigid 1 x 2.5 mm ²
Connecting Capacity Supply Circuit	Rigid 1 x 2.5 mm ²
Couple de serrage	Main Circuit 8 N·m
Groupe de produit	PSTX105
Fonction	Auto phase sequence detection Automatic restart Current limit Current limit ramp Dual current limit Dynamic brake Electricity metering Electronic overload Time-to-cool Emergency mode Event log Full voltage start Jog with slow speed, forward and reverse Keypad password Kick start Limp mode with two-phase motor control if one set of thyristors is shorted Motor heating Pre-start function Pump cleaning Real time clock Sequence start Soft start with torque control Soft start with voltage ramp Soft stop with torque control Soft stop with voltage ramp Stand still brake

Unités

Classifications

Code de classification d'objet	Q
ETIM 7	EC000640 - Soft starter
ETIM 8	EC000640 - Soft starter
ETIM 9	EC000640 - Soft starter
eClass	V11.0 : 27370907
UNSPSC	39121521
Code de catégorie granulaire IDEA (IGCC)	4740 >> Soft starter

Catégories

Produits basse tension → Produits de Contrôle, Protection et sécurité machines → Demarreurs progressifs → Démarreurs progressifs → PSTX Softstarters → PSTX105

Variateurs de vitesse → Demarreurs progressifs → Démarreurs progressifs → PSTX Softstarters → PSTX105

