

DF820

8-way F splitter, 5-2400MHz. Tap loss: 20dB. Pass loss: 1.9dB (862MHz)/3.2dB (2400MHz)

DESCRIPTION

The splitters are compact and feature a shielded cabinet. The QuiCoax connection allows for easy, tool-free installation. Performance is optimal, ensuring a class A + 10 dB rating.



ADVANTAGES

- Precise signal distribution on 8 outputs with 24 dB tap loss
- Wide bandwidth from 5 to 2400 MHz for high-frequency transmission
- Low insertion loss: 1.4 dB at 862 MHz, 2.1 dB at 2300 MHz
- DC current pass-through on the main line for equipment power supply



Updated: 10/07/2026

This document is confidential and is the property of ADALTRA. ADALTRA holds the copyright, and the document must not be copied or modified in any form, in whole or in part, without the prior written permission of ADALTRA. The specifications contained in this document are non-contractual and may be subject to change without prior notice.

CONSTRUCTION & TECHNICAL PERFORMANCE

Output(s)	8
Frequency Band (MHZ)	5-2400
Weight (Kg/U)	0.20

ELECTRICAL CHARACTERISTICS

oui	500
Tap loss (0 to 950 MHz) (dB)	20
Through Loss (2400MHZ) (dB)	<3,2
Through Loss (860MHZ) (dB)	<1,9
Pertes En Outputs Derivees (dB)	20
Protection	>20

TRANSMISSION CHARACTERISTICS

Attenuation (dB)	>10
Frequency Band (MHZ)	5-2400

MECHANICAL CHARACTERISTICS

Type of Connectors	F
--------------------	---

ADDITIONAL INFORMATION

Product Packaging	Bag of 1
Frequency Band (MHZ)	5-2400