

# SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTOR, 17A

Product designation Product type designati	on			Soft Starter ADXB
Motor type				Asynchronous three phase
Electrical features				
Supplies voltage		Time of suntain		Thurshass
		Type of system	\ /	Three phase
		Rated supply voltage	V	208500VAC
		auxiliary supply voltage (Us)		208240VAC
		Rated frequency	Hz	50/60
Rated starter current le	9		Α	17
Rated motor power				
	IEC ratings (T≤40°C)			
		230VAC	kW	4
		400VAC	kW	7.5
		500VAC	KW	9
	UL ratings (T≤40°C)			
		220-240VAC	HP	5
		380-415VAC	HP	7.5
		440-480VAC	HP	10
Number of controlled p	ohases		Nr.	3
Built-in bypass				Yes
Cooling System				Natural
Programming interface	2			ratarar
Display				Backlit LCD 2x16
	-			character
Programming with NFO	C technology			No
Optical port				No
Startup and stop setting	gs			
Startup method				Torque or voltage ramp with current limitation
Stop method				Torque ramp, voltage ramp, free-wheel stop
Braking method				DC dynamic with external relay
Protections				
Auxiliary supply protec	tion			Voltage too low
Power supply Protection				No power, phase loss, phase sequence, frequency out of limits, minimum and maximum voltage





# SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTOR, 17A

Motor protection  Starter protection		Overload at starting (trip class 2, 10A, 10, 15, 20, 25, 30, 35 and 40), overload during running (trip class 2, 10A, 10, 15, 20, 25 and 30), locked rotor, current asymmetry, minimum torque (dry run),  Overcurrent, overtemperature, bypass failure, phase shorted, temperature
		sensor fault,
		maintenance request
Functions		request
Built-in bypass		3
Built-in display and keypad		Yes
Languages		Yes
View measurements		4
Torque control		Yes
Adjustable current limit		Yes
Dynamic braking		Yes
Kick Start function		Yes
Motor overload electronic protection		Yes
Motor protection PTC input		Yes
Protection against phase loss		Yes
Protection against phase inversion		Yes
Protection against locked rotor		Yes
Protection against thyristor overtemperature		Yes
Protection against low load		Yes
Programmable alarm		Yes
Digital inputs		Yes
Analog inputs		Yes
Digital outputs		Yes
Analog output		Yes
Monitoring communication		Yes
Optical port for programming		RS323
Event log		No
Motor hour counter		Yes
Startup counter		Yes
Clock calendar		Yes
Remote external keypad		Yes
Plug-in version Input and Output		Optional
Digital inputs		
Digital Ilipato		3 (2 digital inputs
	Number of digital input N	lr. + 1 digital/analog input)





# SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTÓR, 17A

	Digital input type  Digital input functions	f f 1 ii F ( s a F c ii r t	24VDC (no need or external eeder) I input for start, 1 input or ogrammable stopping, external alarm, motor oreheat, local control, alarms inhibit, manual esetting of motor hermal orotection, second moto
Analog inputs	Number of analog input		I (digital/analog)
	Analog input type	2	0-10VDC (0- 20mA with external resistor 500Ω) Motor protection via PTC probes, acceleration and/or deceleration ramp via analog input, analog input thresholds for motor starting and stopping, analog input thresholds for programmable relay enable
Digital autouta	Analog input functions	v a c r ii ii f a a t	
Digital outputs	Number of digital output	Nr. 4	1
	Digital output arrangement	+ F 2 2	3 x 1 NO (SPST) 1 1 C/O (SPDT) Ratings: 5A 250VAC AC1, 2A 250VAC AC15 C/O output for
Analog outputs	Digital output functions	; ; ; ; ; ; ; ;	global alarm, 3 x INO outputs programmable OFF, motor powered, up to speed, braking, current limit, service required, cascade starting, programmable input thresholds, alarm Axx)



### SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTOR, 17A

Number of analog output Nr.

0...20mA,

Analog output type

4...20mA (0...10V with external resistor  $500\Omega$ ) Current, torque,

motor thermal status, power

Analog output functions

factor and active

power

#### Ambient conditions

#### Temperature

Operating temperature

°C min -10

+55°C (with current derating max

>45°C of 1.5%/ °C)

Storage temperature

°C min -30

°C +70 max 1000 without


derating (over Max altitude m 1000mt with current derating of 0.5%/100m)

95% without Relative humidity % condensation or dripping

Pollution degree 3

# Housing

Mounting		Screw-fixing
IP degree of protection		IP20
Dimensions (W x H x D)	mm	157 x 372 x 223
Weight	Kg	8.97



TYPE	A	В	С	D	E
ADX 0017B	157 (6.18")	372 (14.64")	223 (8.78")	131 (5.16")	357 (14.05")
ADX 0030B	157 (6.18")	372 (14.64")	223 (8.78")	131 (5.16")	357 (14.05")
ADX 0045B	157 (6.18")	372 (14.64")	223 (8.78")	131 (5.16")	357 (14.05")
ADX 0060B	157 (6.18")	534 (21.02")	250 (9.84")	132 (5.20")	517 (20.35")
ADX 0075B	157 (6.18")	534 (21.02")	250 (9.84")	132 (5.20")	517 (20.35")
ADX 0085B	157 (6.18")	534 (21.02")	250 (9.84")	132 (5.20")	517 (20.35")
ADX 0110B	157 (6.18")	584 (22.99")	250 (9.84")	132 (5.20")	567 (22.32")
ADX 0125B	157 (6.18")	584 (22.99")	250 (9.84")	132 (5.20")	567 (22.32")

#### Certifications and compliance

#### Compliance

#### IEC/EN 60947-1



# 51ADX0017B

SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTOR, 17A

IEC/EN 60947-4-2

Certificates

EAC

ETIM classification

ETIM 8.0 EC000640 - Soft starter