



# ROTARY CAM SWITCH 7GN SERIES, MULTI-STEP 1-2-3-4-5-6, 1 POLE 63A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

Product designation				Rotary cam
Product type designation	on			switches 7GN63
General characteristics				7 01100
Switching diagram				85 - Multi-step 1- 2-3-4-6 1 pole
N° of elements				3
Mounting form				U - Front mounting with black handle
Contact characteristics				
Rated insulation voltage	e Ui			
		IEC/EN UL/CSA	V V	690 600
Rated impulse withstan	d voltage Llimp	UL/CSA	kV	6
Conventional free air th			ΚV	
		IEC/EN	Α	63
		UL/CSA	Α	60
Rated operational volta	ge		V	480
Rated operational impu			kV	4
Maximum fuse size for	short-circuit protection In (gG)		_	
		10kA 15kA	A A	63 63
		25kA	A	63
		50kA	A	63
		63kA	Α	63
Rated short time currer	nt Icw			
		1s	Α	1600
Conductivity				10/5 mA/V
Operational current le l				
	AC1/AC21A		Α	63
	AC15		<u> </u>	
	7.010	110V	Α	32
		220/230V	Α	25
		380/400V	Α	15
		660/690V	Α	4
Rated operational power				
	Three-phase AC-3	220/230V	LAAA	11
		380/440V	kW kW	18.5
		500/690V	kW	18.5
	Single-phase AC-3			
		110V	kW	3.7
		220/230V	kW	6.5
		380/440V	kW	11.5
	Three-phase AC23A	220/2201/	1,111	10 F
		220/230V 380/440V	kW kW	12.5 30
		500/690V	kW	30
	Single-phase AC23A			
		110V	kW	3.7
		220/230V	kW	7.5



# ROTARY CAM SWITCH 7GN SERIES, MULTI-STEP 1-2-3-4-5-6, 1 POLE 63A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM


		380/440V	kW	12.5
Rated operational cur				_
	DC21A		_	
		48V	A	63
		60V 110V	A A	50 8
		220V	A	1
	DC23A (poles in series)	220 V		
	2 0 2 0 / ( (poise in conce)	24V	Α	50 (1)
		48V	Α	50 (2)
		60V	Α	50 (3)
		110V	Α	25 (3)
		220V	Α	15 (4)
	DC13			
		24V	Α	63
		48V	Α	40
		60V	A	28
D P		110V	A	3.3
Power dissipation  Mechanical features			W	3.4
Terminals screw				M5
Tightening torque for	terminals may		Nm	2
Conductor size	terrilliais max		INIII	
Conductor Size	AWG - Rigid cable			
	/WC Trigita sabio	min	AWG	14
		Max	AWG	6
	AWG - Flexible cable			_
		min	AWG	14
		Max	AWG	8
	Conductor size (IEC) - Flexible cable			
		min	mm²	2.5
		Max	mm²	10
	Conductor size (IEC) - Rigid cable			
		min	mm²	2.5
Manhaniantiifa		Max	mm²	16
Mechanical life UL technical data			cycles	5x10 <sup>6</sup>
Motor power for direct	t-on-line control			
wotor power for difec	for three-phase motor			
	is. thos phase motor	120V	HP	7.5
		240V	HP	15
		480V	HP	25
		600V	HP	25
	for single-phase motor			
		120V	HP	3
		240V	HP	10
Ambient conditions				
Temperature				
	Operating temperature	_	2.5	25
		min	°C	-25 - 55
	Characte temporature	max	°C	+55
	Storage temperature	min	°C	-40
		min max	°C	-40 +70
		IIIdX		+1U


ROTARY CAM SWITCH 7GN SERIES, MULTI-STEP 1-2-3-4-5-6, 1 POLE 63A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 65X65MM

	AND AUTOMATIC	

Resistance & Protection	
Frontal IP degree	IP40
Terminals IP degree	IP00

#### **Dimensions**






Standard drillings for 7GN125.

Drillings on request for 4 screws fixing (4V version).

Series				Dir	nensi	ons				L Number of elements											
Series	□A	С	ØD	ØD1	ØD2	Е	ØG	□K	□N	1	2	3	4	5	6	7	8	9	10	11	12
7GN12	48	39.5	39	12	5	26.5	38	36	6	36.1	45.8	55.5	65.2	74.9	84.6	94.3	104	113.7	123.4	133.1	142.8
7GN20 48 39.5 39 12 5 26.5 38 36 6 36.1 45.8 55.5 65.2 74.9 84.6 94.3 104							104	113.7	123.4	133.1	142.8										
7GN25								147.3	162.9	176.5	190.1										
7GN32	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN40	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN63	65	53	62	14	5	34.5	58.5	48	7	50.3	68.4	86.5	104.6	122.7	140.8	158.9	177	195.1	213.2	231.3	249.4
7GN125	90	70.5	86	16	6	41.5	84	68	9	67.3	96.4	125.5	154.6	183.7	220.3	249.4	278.5	307.6	336.7	365.8	394.9

### Wiring diagrams



					X	1
			Χ			2
	Χ					3
				Χ		4
		Χ				5 6
X						6
	85					6

#### Certifications and compliance

#### Compliance

CSA C22.2 n° 14

IEC/EN/BS 60947-1

IEC/EN/BS 60947-3

IEC/EN/BS 60947-5-1

UL60947-4-1

### Certificates

cCSAus

EAC

UL

#### ETIM classification

**ETIM 8.0** 

EC001029 -Selector switch, complete