

RZASG125-140MV1

								Compresseur		OFM		IFM		
Intérieur		Extérieur		Alimentation électrique	Plage de tensions	MCA	TOCA	MFA	MSC	RLA	kW	FLA	kW	FLA
FCAG35AVEB	x2	RZASG71M2V1B	50Hz ~ 220-240V	Minimum: 198 V Maximum 264 V	17,6	—	20	—	15,4	0,094	0,9	0,044 x2	0,3 x2	
FCAG71AVEB		RZASG71M2V1B			17,4	—	20	—	15,4	0,094	0,9	0,054	0,4	
FFA35A2VEB	x2	RZASG71M2V1B			17,8	—	20	—	15,4	0,094	0,9	0,050 x2	0,4 x2	
FBA35A2VEB	x2	RZASG71M2V1B			18,2	—	20	—	15,4	0,094	0,9	0,089 x2	0,6 x2	
FBA71A2VEB		RZASG71M2V1B			17,5	—	20	—	15,4	0,094	0,9	0,070	0,5	
FNA35A2VEB	x2	RZASG71M2V1B			17,3	—	20	—	15,4	0,094	0,9	0,034 x2	0,3	
FUA71AVEB		RZASG71M2V1B			17,9	—	20	—	15,4	0,094	0,9	0,046	0,9	
FAA71AUVEB		RZASG71M2V1B			17,4	—	20	—	15,4	0,094	0,9	0,048	0,4	
FVA71AMVEB		RZASG71M2V1B			17,6	—	20	—	15,4	0,094	0,9	0,117	0,6	
FDXM35F3V1B	x2	RZASG71M2V1B			17,6	—	20	—	15,4	0,094	0,9	0,034 x2	0,3 x2	
FHA35AVEB	x2	RZASG71M2V1B			18,2	—	20	—	15,4	0,094	0,9	0,060 x2	0,6 x2	
FHA71AVEB		RZASG71M2V1B			17,8	—	20	—	15,4	0,094	0,9	0,091	0,8	
FCAG35AVEB	x3	RZASG100M7V1B	50Hz ~ 220-240V	Minimum: 198 V Maximum 264 V	21,7	—	25	—	19,0	0,200	1,0	0,044 x3	0,3 x3	
FCAG50AVEB	x2	RZASG100M7V1B			21,4	—	25	—	19,0	0,200	1,0	0,039 x2	0,3 x2	
FCAG100AVEB		RZASG100M7V1B			21,5	—	25	—	19,0	0,200	1,0	0,117	0,7	
FFA35A2VEB	x3	RZASG100M7V1B			22,0	—	25	—	19,0	0,200	1,0	0,050 x3	0,4 x3	
FFA50A2VEB	x2	RZASG100M7V1B			21,6	—	25	—	19,0	0,200	1,0	0,050 x2	0,4 x2	
FBA100A2VEB		RZASG100M7V1B			21,8	—	25	—	19,0	0,200	1,0	0,127	1,0	
FNA35A2VEB	x3	RZASG100M7V1B			21,7	—	25	—	19,0	0,200	1,0	0,034 x3	0,3 x3	
FNA50A2VEB	x2	RZASG100M7V1B			21,8	—	25	—	19,0	0,200	1,0	0,060 x2	0,5 x2	
FUA100AVEB		RZASG100M7V1B			22,2	—	25	—	19,0	0,200	1,0	0,106	1,3	
FAA100AUVEB		RZASG100M7V1B			21,2	—	25	—	19,0	0,200	1,0	0,064	0,4	
FVA100AMVEB		RZASG100M7V1B			22,0	—	25	—	19,0	0,200	1,0	0,238	1,2	
FDXM35F3V1B	x3	RZASG100M7V1B			21,7	—	25	—	19,0	0,200	1,0	0,034 x3	0,3 x3	
FDXM50F3V1B	x2	RZASG100M7V1B			21,8	—	25	—	19,0	0,200	1,0	0,060 x2	0,5 x2	
FHA35AVEB	x3	RZASG100M7V1B			22,7	—	25	—	19,0	0,200	1,0	0,060 x3	0,6 x3	
FHA50AVEB	x2	RZASG100M7V1B			22,0	—	25	—	19,0	0,200	1,0	0,060 x2	0,6 x2	
FHA100AVEB		RZASG100M7V1B			22,2	—	25	—	19,0	0,200	1,0	0,150	1,3	