

RZASG125-140MY1

Intérieur		Extérieur	Alimentation électrique	Plage de tensions		MCA	TOCA	MFA	Compresseur		OFM		IFM	
									MSC	RLA	kW	FLA	kW	FLA
FCAG35AVEB	x4	RZASG125M7Y1B	3N~ 50Hz 380-415V	Minimum: 342 V	Maximum 456 V	12,2	—	16	—	9,5	0,200	1,0	0.044 x4	0.3 x4
FCAG50AVEB	x3	RZASG125M7Y1B				13,0	—	16	—	10,6	0,200	1,0	0.039 x3	0.3 x3
FCAG60AVEB	x2	RZASG125M7Y1B				12,7	—	16	—	10,6	0,200	1,0	0.044 x2	0.3 x2
FCAG125AVEB		RZASG125M7Y1B				14,6	—	16	—	12,0	0,200	1,0	0,168	1,0
FFA35A2VEB	x4	RZASG125M7Y1B				12,6	—	16	—	9,5	0,200	1,0	0.050 x4	0.4 x4
FFA50A2VEB	x3	RZASG125M7Y1B				13,3	—	16	—	10,6	0,200	1,0	0.050 x3	0.4 x3
FFA60A2VEB	x2	RZASG125M7Y1B				13,3	—	16	—	10,6	0,200	1,0	0.050 x2	0.6 x2
FBA35A2VEB	x4	RZASG125M7Y1B				13,4	—	16	—	9,5	0,200	1,0	0.089 x4	0.6 x4
FBA50A2VEB	x3	RZASG125M7Y1B				13,9	—	16	—	10,6	0,200	1,0	0.089 x3	0.6 x3
FBA60A2VEB	x2	RZASG125M7Y1B				13,1	—	16	—	10,6	0,200	1,0	0.070 x2	0.5 x2
FBA125A2VEB		RZASG125M7Y1B				15,1	—	16	—	12,0	0,200	1,0	0,187	1,5
FNA35A2VEB	x4	RZASG125M7Y1B				12,2	—	16	—	9,5	0,200	1,0	0.034 x4	0.3 x4
FNA50A2VEB	x3	RZASG125M7Y1B				13,6	—	16	—	10,6	0,200	1,0	0.060 x3	0.5 x3
FNA60A2VEB	x2	RZASG125M7Y1B				13,1	—	16	—	10,6	0,200	1,0	0.060 x2	0.5 x2
FUA125AVEB		RZASG125M7Y1B				15,0	—	16	—	12,0	0,200	1,0	0,106	1,4
FDA125A5VEB		RZASG125M7Y1B				15,7	—	16	—	12,0	0,200	1,0	0,350	2,1
FVA125AMVEB		RZASG125M7Y1B				14,8	—	16	—	12,0	0,200	1,0	0,238	1,2
FDXM35F3V1B	x4	RZASG125M7Y1B				12,2	—	16	—	9,5	0,200	1,0	0.034 x4	0.3 x4
FDXM50F3V1B	x3	RZASG125M7Y1B				13,6	—	16	—	10,6	0,200	1,0	0.060 x3	0.5 x3
FDXM60F3V1B	x2	RZASG125M7Y1B				13,1	—	16	—	10,6	0,200	1,0	0.060 x2	0.5 x2
FHA35AVEB	x4	RZASG125M7Y1B				13,4	—	16	—	9,5	0,200	1,0	0.060 x4	0.6 x4
FHA50AVEB	x3	RZASG125M7Y1B				13,9	—	16	—	10,6	0,200	1,0	0.060 x3	0.6 x3
FHA60AVEB	x2	RZASG125M7Y1B				13,3	—	16	—	10,6	0,200	1,0	0.091 x2	0.6 x2
FHA125AVEB		RZASG125M7Y1B				15,1	—	16	—	12,0	0,200	1,0	0,150	1,5
FCAG35AVEB	x4	RZASG140M7Y1B	3N~ 50Hz 380-415V	Minimum: 342 V	Maximum 456 V	12,2	—	16	—	9,5	0,200	1,0	0.044 x4	0.3 x4
FCAG50AVEB	x3	RZASG140M7Y1B				12,9	—	16	—	10,5	0,200	1,0	0.039 x3	0.3 x3
FCAG71AVEB	x2	RZASG140M7Y1B				14,4	—	16	—	12,0	0,200	1,0	0.054 x2	0.4 x2
FCAG140AVEB		RZASG140M7Y1B				14,6	—	16	—	12,0	0,200	1,0	0,168	1,0
FFA35A2VEB	x4	RZASG140M7Y1B				12,6	—	16	—	9,5	0,200	1,0	0.050 x4	0.4 x4
FFA50A2VEB	x3	RZASG140M7Y1B				13,2	—	16	—	10,5	0,200	1,0	0.050 x3	0.4 x3
FBA35A2VEB	x4	RZASG140M7Y1B				13,4	—	16	—	9,5	0,200	1,0	0.089 x4	0.6 x4
FBA50A2VEB	x3	RZASG140M7Y1B				13,8	—	16	—	10,5	0,200	1,0	0.089 x3	0.6 x3
FBA71A2VEB	x2	RZASG140M7Y1B				14,6	—	16	—	12,0	0,200	1,0	0.070 x2	0.5 x2
FBA140A2VEB		RZASG140M7Y1B				15,1	—	16	—	12,0	0,200	1,0	0,187	1,5
FNA35A2VEB	x4	RZASG140M7Y1B				12,2	—	16	—	9,5	0,200	1,0	0.034 x4	0.3 x4
FNA50A2VEB	x3	RZASG140M7Y1B				13,5	—	16	—	10,5	0,200	1,0	0.060 x3	0.5 x3
FUA71AVEB	x2	RZASG140M7Y1B				15,4	—	16	—	12,0	0,200	1,0	0.046 x2	0.9 x2
FAA71AUVEB	x2	RZASG140M7Y1B				14,4	—	16	—	12,0	0,200	1,0	0.048 x2	0.4 x2
FVA71AMVEB	x2	RZASG140M7Y1B				14,8	—	16	—	12,0	0,200	1,0	0.117 x2	0.6 x2
FVA140AMVEB		RZASG140M7Y1B				15,0	—	16	—	12,0	0,200	1,0	0,276	1,4
FDXM35F3V1B	x4	RZASG140M7Y1B				12,2	—	16	—	9,5	0,200	1,0	0.034 x4	0.3 x4
FDXM50F3V1B	x3	RZASG140M7Y1B				13,5	—	16	—	10,5	0,200	1,0	0.060 x3	0.5 x3
FHA35AVEB	x4	RZASG140M7Y1B				13,4	—	16	—	9,5	0,200	1,0	0.060 x4	0.6 x4
FHA50AVEB	x3	RZASG140M7Y1B				13,8	—	16	—	10,5	0,200	1,0	0.060 x3	0.6 x3
FHA71AVEB	x2	RZASG140M7Y1B				15,2	—	16	—	12,0	0,200	1,0	0.091 x2	0.8 x2
FHA140AVEB		RZASG140M7Y1B				15,4	—	16	—	12,0	0,200	1,0	0,150	1,8