

PRODUCT-DETAILS

WES/A4.1.1

WES/A4.1.1 Weather Sensor Basic, SM



Informations générales

Extension du type de produit	WES/A4.1.1
Code de produit	2CDG120091R0011
EAN	4016779139519
Description courte	WES/A4.1.1 Weather Sensor Basic, SM
Description longue	The device detects wind speed, rain, brightness in 4 directions (with Weather Unit WZ/S1.3.1.2 maximum 3 directions can be evaluated), twilight, temperature, day/night and over GPS signal date and time. An additional heating transformer is not needed.

Installation

Instructions et manuels	2CDG941266P0001
-------------------------	-----------------

Technique

Fiche produit, informations techniques	9AKK108464A0416
Compatible Bus Systems	KNX (TP)
Product Range	KNX
Type de montage	Surface Mounted
Manual Operation	Non

Additional Information	Heater included
Couleur	white matt
Nombre de batteries	0
Application Function	Blind / Shutter / Shading Control

Environnement

Indice de protection	IP44
Statut RoHS	Following EU Directive 2011/65/EU
Informations RoHS	9AKK108464A0588
REACH Declaration	9AKK108468A9644
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363

Dimensions

Produit Largeur Net	102 mm
Produit Hauteur Net	105 mm
Produit Longueur Net	102 mm
Poids net	0.162 kg

Commande

ID du produit remplacé	WES/A3.1
------------------------	----------

Certificats et Déclarations (Numéro de document)

Déclaration de Conformité - CE	9AKK108464A0588
Declaration of Conformity - UKCA	9AKK108464A0589

Classifications

ETIM 8	EC000926 - Physical sensor for bus system
ETIM 9	EC000926 - Physical sensor for bus system
Catégorie DEEE	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer
CN8	9025 80 40
eClass	V11.0 : 27143137
Code de classification d'objet	A

Accessories

Identifier	Description	Type	Quantity	Unit Of Measure
2CDG110184R0011	WZ/S1.3.1.2 Weather Unit, MDRC	WZ/S 1.3.1.2	1	piece
2CDG120088R0011	WB/Z1.1.1 Wall Mounting Adapter for WES/A4.1.1	WB/Z1.1.1	1	piece

Catégories

Produits basse tension → Home and Building Automation → KNX → Standard Inputs → Metrological and Physical Sensors

