OSRAM

ORIGINAL - METAL BASE H6W

Original spare part





The cost-effective original spare parts

ORIGINAL signal lamps with metal bases feature - like all ORIGINAL products from OSRAM - a reliable OEM quality. Due to the wide product range, the lamps can be used as original spare lamps for different applications.

Technical data

Product information

Order reference	64132	
Application (Category and Product specific)	Auxiliary lamp	


Electrical data

Power input	7 W
Nominal voltage	12.0 V
Nominal wattage	6.00 W
Test voltage	13.5 V
Power input tolerance	±5 %

Photometrical data

Luminous flux	125 lm
Luminous flux tolerance	±12 %

Dimensions & weight







Diameter	9 mm
Product weight	2.30 g
Length	33.0 mm

Lifespan

Lifespan B3	350 h
Lifespan Tc	700 h

Additional product data

Base (standard designation)	BAX9s
-----------------------------	-------

Capabilities

Technology	AUX

Certificates & standards

ECE category	H6W	
Approval marks – approval	E1 approval	

Country specific categorizations

Order reference	64132

Country specific information

Product code	METEL code	SEG-No.	STK-Number	UK Org
4008321094896	OSRA64132	-	-	-
4008321094902	OSRA64132	-	-	-
4008321094896	OSRA64132	-	-	-

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321094896	ORIGINAL - METAL BASE H6W	Unpacked 1	35 mm x 15 mm x 18 mm	0.01 dm³	21.00 g
4008321094902	ORIGINAL - METAL BASE H6W	Folding carton box 10	54 mm x 40 mm x 138 mm	0.30 dm ³	36.00 g
4008321094919	ORIGINAL - METAL BASE H6W	Shipping carton box 50	205 mm x 144 mm x 64 mm	1.89 dm ³	230.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.















OSRAM