

ORIGINAL - METAL BASE H21W

Original spare part



The cost-effective original spare parts for motorcycles

Discover OSRAM's ORIGINAL signal lamps with metal bases - high-quality original spare parts for motorcycle lamps. Due to the wide product range, the lamps can be used for different applications. Use these lamps for example as position and parking lights or for number plate and side position lights of your motorcycle.

Product datasheet

Technical data

Product information

Order reference	64136
Application (Category and Product specific)	Auxiliary lamp


Electrical data

Power input	25 W
Nominal voltage	12.0 V
Nominal wattage	21.00 W
Power input tolerance	±5 %
Test voltage	13.5 V

Photometrical data

Luminous flux	600 lm
Luminous flux tolerance	±12 %

Dimensions & weight



Length	38.9 mm
Diameter	9 mm
Product weight	2.68 g

Lifespan

Lifespan B3	240 h
Lifespan Tc	480 h

Additional product data

Base (standard designation)	BAY9s
-----------------------------	-------

Product datasheet

Capabilities

Technology	AUX
------------	-----

Certificates & standards

ECE category	H21W
--------------	------

Country specific categorizations

Order reference	64136
-----------------	-------

Country specific information

Product code	METEL code	SEG-No.	STK-Number	UK Org
4008321095190	OSRA64136	-	-	-
4008321095206	OSRA64136	-	-	-
4008321095190	OSRA64136	-	-	-

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4008321095190	ORIGINAL - METAL BASE H21W	Unpacked 1	- x - x -		
4008321095206	ORIGINAL - METAL BASE H21W	Folding carton box 10	54 mm x 40 mm x 138 mm	0.30 dm ³	39.80 g
4008321095213	ORIGINAL - METAL BASE H21W	Shipping carton box 50	205 mm x 144 mm x 64 mm	1.89 dm ³	249.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.



OSRAM