

AAQCF182

Apartment amplifier 1 input 47-694 MHz gain 18 dB**DESCRIPTION**

APARTMENT AMPLIFIERS. 1-input apartment amplifier, frequency band 47-694 MHz compatible with standard TV, with a high gain of 18 dB for effective amplification. Equipped with QC/F connectors ensuring reliable connection and low power consumption of 0.9 W, it optimizes TV reception in residential installations.

**ADVANTAGES**

- Effective TV signal amplification with 18 dB gain on 47-694 MHz
- QC/F connectors ensuring reliable connection
- Low power consumption of 0.9 W suitable for residential installations
- High output level of 2 x 110 dB μ V for good coverage



Updated: 10/07/2026

This document is confidential and is the property of ADALTRA. ADALTRA holds the copyright, and the document must not be copied or modified in any form, in whole or in part, without the prior written permission of ADALTRA. The specifications contained in this document are non-contractual and may be subject to change without prior notice.

CONSTRUCTION & TECHNICAL PERFORMANCE

Input(s)	1
Output(s)	4
Frequency Band (MHZ)	47-694
Noise Figure (dB)	< 3
Weight (Kg/U)	0.50

ELECTRICAL CHARACTERISTICS

Power Consumption	0.9
Noise Figure (dB)	< 3
Gain (dB)	18
Output Level (dBμv)	2 x 110
Return Loss (dB)	> 10
Supply Voltage (Vac)	100- 240

TRANSMISSION CHARACTERISTICS

Attenuation (dB)	10
Frequency Band (MHZ)	47-694

MECHANICAL CHARACTERISTICS

Connector (Type)	QC / F
------------------	--------

ADDITIONAL INFORMATION

Frequency Band (MHZ)	47-694
----------------------	--------