

## PAR 38 - LED 15W



Lampe réflecteur Ø122.

 PAR38 LED
  230V
  30° 35 000 h

P (W)	Culot	Lumens	Teinte	Code
15	E27	1350	○ 4000 K	<b>2980</b>
15	E27	1350	● 3000 K	<b>2995</b>

PAR 38 LED	4000 K	15 W	30°
	h (m)	E <sub>max</sub> (lx)	d (m)
	1	2172	0,54
	2	543	1,1
	3	241	1,6
	4	136	2,1
	5	87	2,7

PAR 38 LED	3000 K	15 W	30°
	h (m)	E <sub>max</sub> (lx)	d (m)
	1	2172	0,54
	2	543	1,1
	3	241	1,6
	4	136	2,1
	5	87	2,7

La technologie des lampes LED progressant rapidement, la puissance (W) est susceptible d'être inférieure à celle indiquée tout en conservant un flux lumineux (lm) équivalent ou supérieur. Nos produits peuvent être modifiés afin de les adapter aux meilleures performances disponibles.

## CES LAMPES CONVIENNENT POUR :

<p><b>EN 63 &gt; lampe R63</b></p>  <p>Code : <b>0612</b></p>	<p><b>EN 80 &gt; lampe R80</b></p>  <p>Code : <b>0614</b></p>
<p><b>MANTA R63 &gt; lampe R63</b></p>  <p>Code : <b>0669</b></p>	<p><b>MANTA R80 &gt; lampe R80</b></p>  <p>Code : <b>0691</b></p>
<p><b>TURBO R80 &gt; lampe R80</b></p>  <p>Code : <b>0617</b></p>	<p><b>DAFNEE &gt; lampe PAR 38</b></p>  <p>Code : <b>0790</b></p>