

WTB4SC-3P2262A70

**MINIATURE PHOTOELECTRIC SENSORS** 





#### Illustration may differ

# Ordering information

Туре	Part no.
WTB4SC-3P2262A70	1067756

The sensor is equipped with a special Smart Task function. Additional information can be found in the "Technical Data." Use of the sensor for pure object detection is limited.

Other models and accessories → www.sick.com/W4





### Detailed technical data

### **Features**

Functional principle	Photoelectric proximity sensor
Functional principle detail	Background suppression
Sensing range max.	4 mm 180 mm <sup>1)</sup>
Sensing range	10 mm 180 mm <sup>1)</sup>
Emitted beam	
Light source	PinPoint LED <sup>2)</sup>
Type of light	Visible red light
Light spot size (distance)	Ø 6.5 mm (150 mm)
Key LED figures	
Wave length	650 nm
Adjustment	IO-Link, Single teach-in button
Pin 2 configuration	External input, Teach-in input, Sender off input, Detection output, logic output

 $<sup>^{1)}</sup>$  Object with 90% remission (based on standard white, DIN 5033).

## Safety-related parameters

MTTF <sub>D</sub>	873 years
DC <sub>avg</sub>	0 %

 $<sup>^{2)}</sup>$  Average service life: 100,000 h at  $T_U$  = +25 °C.

### Communication interface

IO-Link	<b>√</b> , COM2 (38,4 kBaud)
Data transmission rate	COM2 (38,4 kBaud)
Cycle time	2.3 ms
Process data length	16 Bit
Process data structure	Bit 0 = switching signal $Q_{L1}$ Bit 1 = switching signal $Q_{L2}$ Bit 2 15 = measuring value
VendorID	26
DeviceID HEX	0x8000D3
DeviceID DEC	8388819

### Electrical data

10 V DC 30 V DC <sup>1)</sup>
< 5 V <sub>pp</sub> <sup>2)</sup>
30 mA <sup>3)</sup>
III
PNP <sup>4)</sup>
Light/dark switching
≤ 100 mA
150 μs <sup>5)</sup>
1,000 Hz
A <sup>6)</sup> B <sup>7)</sup> C <sup>8)</sup> D <sup>9)</sup>
300 μs 450 μs <sup>10) 5)</sup>
1,000 Hz <sup>11)</sup>

 $<sup>^{1)}</sup>$  Limit values when operated in short-circuit protected network: max. 8 A.

#### Mechanical data

Housing	Rectangular
Design detail	Slim
Dimensions (W x H x D)	12.2 mm x 41.8 mm x 17.3 mm
Connection	Male connector M8, 4-pin
Material	

 $<sup>^{2)}\,\</sup>text{May}$  not exceed or fall below  $\text{U}_{\text{V}}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{\</sup>rm 4)}$  Pin 4: This switching output must not be connected to another output.

 $<sup>^{5)}</sup>$  Valid for Q  $\backslash$  on Pin2, if configured with software.

 $<sup>^{6)}</sup>$  A = V<sub>S</sub> connections reverse-polarity protected.

 $<sup>^{7)}</sup>$  B = inputs and output reverse-polarity protected.

<sup>8)</sup> C = interference suppression.

<sup>&</sup>lt;sup>9)</sup> D = outputs overcurrent and short-circuit protected.

<sup>10)</sup> Signal transit time with resistive load.

 $<sup>^{11)}</sup>$  With light / dark ratio 1:1, valid for Q  $\backslash$  on Pin2, if configured with software.

# MINIATURE PHOTOELECTRIC SENSORS

Housing	Plastic, ABS
Front screen	Plastic, PMMA
Weight	20 g

## Ambient data

Enclosure rating	IP67 IP66
Ambient operating temperature	-40 °C +60 °C
Ambient temperature, storage	-40 °C +75 °C
UL File No.	NRKH.E181493 & NRKH7.E181493

### **Smart Task**

Smart Task name	Time measurement + debouncing	
Logic function	Direct WINDOW	
Timer function	Deactivated On delay Off delay ON and OFF delay Impulse (one shot)	
Inverter	Yes	
Response time	1) 2)	
Repeatability	1) 2)	
Time measurement accuracy	SIO Direct: — SIO Logic: - 0,7 + 0,7 ms $\pm$ 0,5 % of time measurement value IOL: - 0.9 + 0.9 ms $\pm$ 0.5% of the time measurement	
Time measurement accuracy (e.g. accuracy for time measurement value = 1 s )	SIO Direct: SIO Logic: - 5,7 + 5,7 ms IOL: - 5,9 + 5,9 ms	
Resolution time measuring value	1 ms	
Min. Time between two process events (switches)	SIO Direct: SIO Logic: 500 µs IOL: 800 µs	
Debounce time max.	SIO Direct: SIO Logic: 30.000 ms IOL: 30.000 ms	
Switching signal		
Switching signal Q <sub>L1</sub>	Output type (dependant on the adjusted threshold)	
Switching signal Q <sub>L2</sub>	Output type (dependant on the adjusted threshold)	
Measuring value	Time measurement value	

 $<sup>^{1)}\,</sup>SIO\,\,Logic:\,Sensor\,\,operation\,\,in\,\,standard\,\,I/O\,\,mode\,\,without\,\,IO-Link\,\,communication.\,\,Sensor-internal\,\,logic\,\,or\,\,timing\,\,parameters\,\,plus\,\,Automation\,\,Functions\,\,used.$ 

# Diagnosis


Device status	Yes	
Classifications		
ECLASS 5.0	27270904	
ECLASS 5.1.4	27270904	
ECLASS 6.0	27270904	

<sup>2)</sup> IOL: Sensor operation with full IO-Link communication and usage of logic, timing and Automation Function parameters.

ECLASS 6.2	27270904
ECLASS 7.0	27270904
ECLASS 8.0	27270904
ECLASS 8.1	27270904
ECLASS 9.0	27270904
ECLASS 10.0	27270904
ECLASS 11.0	27270904
ECLASS 12.0	27270903
ETIM 5.0	EC002719
ETIM 6.0	EC002719
ETIM 7.0	EC002719
ETIM 8.0	EC002719
UNSPSC 16.0901	39121528

# Connection diagram


Cd-367



#### Characteristic curve

WTB4S-3, 180 mm

% of sensing distance




Distance in mm (inch)

- ① Sensing range on black, 6% remission factor
- ② Sensing range on gray, 18% remission factor
- 3 Sensing range on white, 90% remission factor

## Sensing range diagram


WTB4S-3, 180 mm



- Sensing range max.
- Sensing range
- ① Sensing range on black, 6% remission factor
- ② Sensing range on gray, 18% remission factor
- 3 Sensing range on white, 90% remission factor

# Dimensional drawing (Dimensions in mm (inch))

## WTB4S-3, Single teach-in button



- ① Standard direction of the material being detected
- ② Optical axis, receiver
- 3 Optical axis, sender
- ④ LED indicator green: Supply voltage active
- (5) LED indicator yellow: Status of received light beam
- ⑥ Teach-in button
- Threaded mounting hole M3
- ® Connection

### Recommended accessories

Other models and accessories → www.sick.com/W4

	Brief description	Туре	Part no.
Distributors			
	<ul> <li>Connection type head A: Male connector, M12, 4-pin, A-coded</li> <li>Connection type head B: Female connector, M8, 4-pin, A-coded</li> <li>Connection type head C: Female connector, M8, 4-pin, A-coded</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 0.11 m, PVC</li> <li>Description: Sensor/actuator cable, Y-distribution, 2 x M8 female connectors, 4-pin, straight, 0.11 m, PVC cable, 1 x M12 male connector, 4-pin, straight, connects a SICK sensor to a SICK Smart sensor; Female connector brassed (A): Auxiliary sensor; Female connector nickel-plated (B): Smart Sensor; Male connector nickel-plated (C): IO-Link master/ PLC</li> <li>Note: Slimline T-piece, 2 x M8 female connector + M12 male connector with cable</li> </ul>	SYL-8204-G0M11-X2	6055012
Mounting brackets and plates			
20	Mounting bracket for wall mounting, Stainless steel 1.4571, mounting hardware included	BEF-W4-A	2051628

# WTB4SC-3P2262A70 | W4

# MINIATURE PHOTOELECTRIC SENSORS

	Brief description	Туре	Part no.
Others			
	<ul> <li>Connection type head A: Female connector, M8, 4-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 4-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals</li> </ul>	YF8U14- 050VA3XLEAX	2095889
100	<ul> <li>Connection type head A: Female connector, M8, 4-pin, straight, A-coded</li> <li>Connection type head B: Male connector, M12, 4-pin, straight, A-coded</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 4-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals</li> </ul>	YF8U14- 050VA3M2A14	2096609

## Recommended services

Additional services → www.sick.com/W4

	Туре	Part no.
Function Block Factory		
<ul> <li>Description: The Function Block Factory supports common programmable logic controllers (PLCs) from various manufacturers, such as Siemens, Beckhoff, Rockwell Automation and B&amp;R. More information on the FBF can be found <a href="https://fbf.cloud.sick.com" target="_blank">here</a>.</li> <li>Note: You can configure your function block at <a href="https://fbf.cloud.sick.com" target="_blank">Function Block Factory.</a> As a login please use your SICK ID.</li> </ul>	Function Block Factory	On request

# SICK AT A GLANCE

SICK is one of the leading manufacturers of intelligent sensors and sensor solutions for industrial applications. A unique range of products and services creates the perfect basis for controlling processes securely and efficiently, protecting individuals from accidents and preventing damage to the environment.

We have extensive experience in a wide range of industries and understand their processes and requirements. With intelligent sensors, we can deliver exactly what our customers need. In application centers in Europe, Asia and North America, system solutions are tested and optimized in accordance with customer specifications. All this makes us a reliable supplier and development partner.

Comprehensive services complete our offering: SICK LifeTime Services provide support throughout the machine life cycle and ensure safety and productivity.

For us, that is "Sensor Intelligence."

# **WORLDWIDE PRESENCE:**

Contacts and other locations -www.sick.com

