

WT34-B420 W34

**COMPACT PHOTOELECTRIC SENSORS** 





### Ordering information

Туре	Part no.
WT34-B420	1019230

Other models and accessories → www.sick.com/W34

Illustration may differ





#### Detailed technical data

#### **Features**

Functional principle	Photoelectric proximity sensor
Functional principle detail	Background suppression
Dimensions (W x H x D)	27 mm x 92 mm x 70 mm
Housing design (light emission)	Rectangular
Sensing range max.	100 mm 2,500 mm <sup>1)</sup>
Sensing range	100 mm 2,500 mm
Type of light	Infrared light
Light source	LED <sup>2)</sup>
Light spot size (distance)	Ø 80 mm (2,500 mm)
Adjustment	Potentiometer

 $<sup>^{1)}</sup>$  Object with 90% remission (based on standard white, DIN 5033).

### Mechanics/electronics

Supply voltage U <sub>B</sub>	10 V DC 30 V DC <sup>1)</sup>
Ripple	< 5 V <sub>pp</sub> <sup>2)</sup>
Current consumption	50 mA
Switching output	NPN, PNP
Switching mode	Light switching, Dark switching

<sup>1)</sup> Limit values.

 $<sup>^{2)}</sup>$  Average service life: 100,000 h at T<sub>U</sub> = +25 °C.

 $<sup>^{2)}\,\</sup>mathrm{May}$  not exceed or fall below  $\mathrm{U}_{\mathrm{V}}$  tolerances.

 $<sup>^{</sup>m 3)}$  Signal transit time with resistive load.

 $<sup>^{4)}</sup>$  With light/dark ratio 1:1.

 $<sup>^{5)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>6)</sup> C = interference suppression.

<sup>&</sup>lt;sup>7)</sup> D = outputs overcurrent and short-circuit protected.

<sup>8)</sup> Reference voltage: 50 V DC.

Switching mode selector	Selectable via PNP/NPN selector
Output current I <sub>max.</sub>	≤ 100 mA
Response time	≤ 500 µs <sup>3)</sup>
Switching frequency	1,000 Hz <sup>4)</sup>
Time functions	On delayoff delayadjustable
Delay time	Adjustable via time delay selector switch, 0.5 s 10 s
Connection type	Male connector M12, 4-pin
Circuit protection	A <sup>5)</sup> C <sup>6)</sup> D <sup>7)</sup>
Protection class	II <sup>8)</sup>
Weight	140 g
Housing material	Plastic, ABS
Enclosure rating	IP67
Test input sender off	TE to 0 V
Ambient operating temperature	-40 °C +60 °C
Ambient temperature, storage	-40 °C +75 °C
UL File No.	NRKH.E181493 & NRKH7.E181493

<sup>1)</sup> Limit values.

## Safety-related parameters

MTTFD	564 years
<b>DC</b> <sub>avg</sub>	0 %
T <sub>M</sub> (mission time)	20 years

### Classifications

ECLASS 5.0	27270904
ECLASS 5.1.4	27270904
ECLASS 6.0	27270904
ECLASS 6.2	27270904
ECLASS 7.0	27270904
ECLASS 8.0	27270904
ECLASS 8.1	27270904
ECLASS 9.0	27270904
ECLASS 10.0	27270904
ECLASS 11.0	27270904
ECLASS 12.0	27270903

 $<sup>^{2)}</sup>$  May not exceed or fall below  $\mathrm{U}_{\mathrm{V}}$  tolerances.

<sup>&</sup>lt;sup>3)</sup> Signal transit time with resistive load.

<sup>4)</sup> With light/dark ratio 1:1.
5) A = V<sub>S</sub> connections reverse-polarity protected.

<sup>6)</sup> C = interference suppression.

<sup>7)</sup> D = outputs overcurrent and short-circuit protected.


<sup>8)</sup> Reference voltage: 50 V DC.

# WT34-B420 | W34

## COMPACT PHOTOELECTRIC SENSORS


ETIM 5.0	EC002719
ETIM 6.0	EC002719
ETIM 7.0	EC002719
ETIM 8.0	EC002719
UNSPSC 16.0901	39121528

# Dimensional drawing (Dimensions in mm (inch))



- ① Alignment sight② LED signal strength indicator
- 3 Standard direction of the material being detected
- ④ Center of optical axis, sender
- ⑤ Center of optical axis, receiver (close range)
- Center of optical axis, receiver (far range)
- 7 Mounting hole ø 5.5 mm, for M5 hexagon nuts on both sides

### Adjustments



- ② LED signal strength indicator
- Adjustment of sensing range
- ① Light/dark selector
- ① NPN/PNP changeover switch
- ② Time control t<sub>2</sub>= OFF delay
- Time delay selector switch


### Connection type




### Connection diagram

Cd-117

#### Characteristic curve



## Sensing range diagram



1	Scanning distance on black <sup>9)</sup>
2	Scanning distance on grey 9)
3	Scanning distance on white <sup>9)</sup>

#### Recommended accessories

Other models and accessories → www.sick.com/W34

	Brief description	Туре	Part no.
Mounting brackets and plates			
	Mounting bracket, Stainless steel (1.4301), mounting hardware included	BEF-WN-W24	2015248
Plug connectors and cables			
	<ul> <li>Connection type head A: Male connector, M12, 4-pin, straight</li> <li>Description: Unshielded</li> <li>Connection systems: Screw-type terminals</li> <li>Permitted cross-section: ≤ 0.75 mm²</li> </ul>	STE-1204-G	6009932

	Brief description	Туре	Part no.
Others			
	<ul> <li>Connection type head A: Female connector, M12, 4-pin, straight, A-coded</li> <li>Connection type head B: Flying leads</li> <li>Signal type: Sensor/actuator cable</li> <li>Cable: 5 m, 4-wire, PVC</li> <li>Description: Sensor/actuator cable, unshielded</li> <li>Application: Zones with chemicals</li> </ul>	YF2A14- 050VB3XLEAX	2096235

# SICK AT A GLANCE

SICK is one of the leading manufacturers of intelligent sensors and sensor solutions for industrial applications. A unique range of products and services creates the perfect basis for controlling processes securely and efficiently, protecting individuals from accidents and preventing damage to the environment.

We have extensive experience in a wide range of industries and understand their processes and requirements. With intelligent sensors, we can deliver exactly what our customers need. In application centers in Europe, Asia and North America, system solutions are tested and optimized in accordance with customer specifications. All this makes us a reliable supplier and development partner.

Comprehensive services complete our offering: SICK LifeTime Services provide support throughout the machine life cycle and ensure safety and productivity.

For us, that is "Sensor Intelligence."

# **WORLDWIDE PRESENCE:**

Contacts and other locations -www.sick.com

