

ROTARY CAM SWITCH 7GN SERIES, CHANGEOVER SWITCH WITHOUT 0, 3 POLES 16A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM



Description description			Rotary cam
Product designation			switches
Product type designation			7GN12
General characteristics			
O Maldan Parama			56 - Changeover
Switching diagram			switch without 0 3 poles
N° of elements			2
14 Of Clements			U - Front
Mounting form			mounting with
3			black handle
Contact characteristics			
Rated insulation voltage Ui			
	IEC/EN	V	690
	UL/CSA	V	600
Rated impulse withstand voltage Uimp		kV	6
Conventional free air thermal current Ith			
	IEC/EN	Α	16
	UL/CSA	A	15
Rated operational voltage		V	480
Rated operational impulse voltage		kV	4
Maximum fuse size for short-circuit protection In (gG)	401.4		40
	10kA	A	16
	15kA 25kA	A A	10 10
Rated short time current lcw	ZOKA	A	10
Nated Short time current low	1s	Α	200
Conductivity	13		10/5 mA/V
Operational current le IEC/EN			10/3 111/4 4
AC1/AC21A			
110 11/102 11/1		Α	16
AC15			
	110V	Α	10
	220/230V	Α	8
	380/400V	Α	4
	660/690V	Α	1.5
Rated operational power in AC			
Three-phase AC-3			
	220/230V	kW	2.5
	380/440V	kW	4
0.1.1.2.2	500/690V	kW	5.5
Single-phase AC-3	44014		0.0
	110V	kW	0.8
	220/230V 380/440V	kW kW	1.5 2.2
Three-phase AC23A	300/4407	r.vv	۷.۷
THIEE-phase AC23A			



ROTARY CAM SWITCH 7GN SERIES, CHANGEOVER SWITCH WITHOUT 0, 3 POLES 16A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM


		220/230V	kW	3
		380/440V	kW	5.5
		500/690V	kW	7.5
	Single-phase AC23A	300/030 V	IXVV	7.0
	Single-phase AO23A	4401/	1.3.47	0.0
		110V	kW	0.8
		220/230V	kW	1.7
		380/440V	kW	3
Rated operational of	current in DC			
•	DC21A			
		48V	Α	12
		60V	A	12
		110V		4
			A	
		220V	Α	0.6
		440V	Α	0.25
	DC23A (poles in series)			
		24V	Α	10 (1)
		48V	Α	10 (2)
		60V	A	10 (3)
		110V	A	
				5 (3)
		220V	Α	5 (4)
	DC13			
		24V	Α	12
		48V	Α	10
		60V	Α	8
		110V	Α	1
		220V	A	0.4
		440V	A	0.15
Power dissipation			W	0.8
Mechanical features	S			
Terminals screw				M3
Tightening torque for	or terminals max		Nm	0.5
Conductor size				
	AWG - Rigid cable			
	71170 Trigia dable	min	AWG	20
		Max	AWG	12
	AWG - Flexible cable			
		min	AWG	20
		Max	AWG	14
	Conductor size (IEC) - Flexible cable			
		min	mm²	0.5
		Max	mm²	2.5
	Condustor size (IEC) Digid coble	IVIAX	111111	۷.0
	Conductor size (IEC) - Rigid cable	-	_	0.5
		min	mm²	0.5
		Max	mm²	2.5
Mechanical life			cycles	3x10 ⁶
UL technical data				
Motor power for dire	ect-on-line control			
otor potror for all				
	for three-phase motor			
	for three-phase motor	40014	L/D	4 5
	for three-phase motor	120V	HP	1.5
	for three-phase motor	240V	HP	3
	for three-phase motor			
	for three-phase motor	240V	HP	3
		240V 480V	HP HP	3 50
	for three-phase motor for single-phase motor	240V 480V 600V	HP HP HP	3 50 40
		240V 480V	HP HP	3 50



ROTARY CAM SWITCH 7GN SERIES, CHANGEOVER SWITCH WITHOUT 0, 3 POLES 16A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM

		240V	HP	1
Ambient conditions				
Temperature				
•	Operating temperature			
		min	°C	-25
		max	°C	+55
	Storage temperature			_
		min	°C	-40
		max	°C	+70
Resistance & Protect	ion			
Frontal IP degree				IP40
Terminals IP degree				IP00
Dimensions				


9 Q



Standard drillings for 7GN125.
Drillings on request for 4 screws fixing (4V version).

Carias		Dimensions								L Number of elements											
Series	ΠA	С	ØD	ØD1	ØD2	Е	ØG	□K	□N	1	2	3	4	5	6	7	8	9	10	11	12
7GN12	48	39.5	39	12	5	26.5	38	36	6	36.1	45.8	55.5	65.2	74.9	84.6	94.3	104	113.7	123.4	133.1	142.8
7GN20	48	39.5	39	12	5	26.5	38	36	6	36.1	45.8	55.5	65.2	74.9	84.6	94.3	104	113.7	123.4	133.1	142.8
7GN25	48	39.5	43	12	5	26.5	38	36	6	40.5	54.1	67.7	81.3	94.9	108.5	122.1	135.7	147.3	162.9	176.5	190.1
7GN32	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN40	65	53	58	14	5	34.5	58.5	48	7	46.5	61.6	76.7	91.8	106.9	122	137.1	152.2	167.3	182.4	197.5	212.6
7GN63	65	53	62	14	5	34.5	58.5	48	7	50.3	68.4	86.5	104.6	122.7	140.8	158.9	177	195.1	213.2	231.3	249.4
7GN125	90	70.5	86	16	6	41.5	84	68	9	67.3	96.4	125.5	154.6	183.7	220.3	249.4	278.5	307.6	336.7	365.8	394.9

Wiring diagrams



Certifications and compliance

Compliance

CSA C22.2 n° 14

IEC/EN/BS 60947-1

IEC/EN/BS 60947-3

IEC/EN/BS 60947-5-1

UL60947-4-1

Certificates



7GN1256U

ROTARY CAM SWITCH 7GN SERIES, CHANGEOVER SWITCH WITHOUT 0, 3 POLES 16A, FOR FRONT MOUNTING WITH BLACK HANDLE, FRONT PLATE 48X48MM

EAC	
UL	

ETIM classification

ETIM 8.0

EC001029 -Selector switch, complete