**ENERGY AND AUTOMATION** 

## ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH WITHOUT 0, 3 POLES 20A, FOR FRONT MOUNTING WITHOUT FRONT PLATE WITH KEY OPERATION FOR HOLE Ø22MM FIXING

Product designation				Rotary cam switches
Product type designat	tion			GX20
General characteristic				
Switching diagram				56 - Changeover switch without 0 3 poles
N° of elements				3
Mounting form  Contact characteristic	c			U12 - Front mounting without front plate with key operation for hole diam. 22mm fixing
Rated insulation voltage				
Rated impulse withsta		IEC/EN UL/CSA	V V kV	690 600
Conventional free air t	· · · · · · · · · · · · · · · · · · ·		KV	0
Conventional free all t	nemai current iui	IEC/EN UL/CSA	A A	20 15
Rated operational volt	tage		V	440
Rated operational imp	oulse voltage		kV	4
Maximum fuse size fo	r short-circuit protection In (gG)			
		10kA	Α	20
		15kA	Α	20
<del></del>		25kA	Α	20
Rated short time curre	ent ICW	1s	Α	250
Conductivity				10/5 mA/V
Operational current le	AC1/AC21A		A	20
	AC15			20
		110V 220/230V 380/400V	A A	10 8 6
		660/690V	A A	1.5
Rated operational pov	ver in AC	330/030 V	,,	
Tanta aparational pov	Three-phase AC-3			
		220/230V	kW	3.7
		380/440V	kW	5.5
		500/690V	kW	5.5
	Single-phase AC-3			
		110V	kW	0.75
		220/230V	kW	1.8
	<del>-</del>	380/440V	kW	3
	Three-phase AC23A	000/0001	1387	4
		220/230V	kW	4
		380/440V 500/690V	kW kW	7.5
	Single-phase AC23A	300/0907	r.vv	7.5
	onigio priaso AozoA	110V	kW	0.75
				<u> </u>



**ENERGY AND AUTOMATION** 

ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH WITHOUT 0, 3 POLES 20A, FOR FRONT MOUNTING WITHOUT FRONT PLATE WITH KEY OPERATION FOR HOLE Ø22MM **FIXING** 

		220/230V	kW	2.2
		380/440V	kW	3.5
Rated operational curr				
	DC21A			
		48V	Α	20
		60V	A	20
		110V	A	4
		220V	A	0.6
	DC23A (poles in series)	440V	A	0.25
	DC25A (poles in series)	24V	Α	20 (1)
		48V	A	20 (1)
		60V	A	20 (2)
		110V	A	10 (3)
		220V	Α	8 (4)
	DC13	<u> </u>		- ( )
		24V	Α	20
		48V	Α	16
		60V	Α	12
		110V	Α	1
		220V	Α	0.4
		440V	Α	0.15
Power dissipation			W	0.6
Mechanical features				
Terminals screw				M3
Tightening torque for to	erminals max		Nm	0.8
Conductor size				
	AWG - Rigid cable			
		min	AWG	20
		Max	AWG	12
	AWG - Flexible cable		414/0	00
		min	AWG	20
	Conductor size (IEC) Florible coble	Max	AWG	12
	Conductor size (IEC) - Flexible cable	min	mm²	0.5
		min Max	mm²	2.5
	Conductor size (IEC) - Rigid cable	IVIdX	111111	۷.5
	Solidation Size (IEO) - Migia Cable	min	mm²	0.5
		Max	mm²	2.5
Mechanical life		· · · · · · · · · · · · · · · · · · ·	cycles	1X10 <sup>6</sup>
UL technical data			- <b>,</b>	
Motor power for direct	-on-line control			
·	for three-phase motor			
	•	120V	HP	1.5
		240V	HP	3
		480V	HP	5
		600V	HP	5
	for single-phase motor			
		120V	HP	0.75
		240V	HP	1.5
Ambient conditions				
Temperature				
	Operating temperature			
		min	°C	-25




**ENERGY AND AUTOMATION** 

ROTARY CAM SWITCH GX SERIES, CHANGEOVER SWITCH WITHOUT 0, 3 POLES 20A, FOR FRONT MOUNTING WITHOUT FRONT PLATE WITH KEY OPERATION FOR HOLE Ø22MM FIXING

	max	°C	+55	
Storage temperature				
	min	°C	-40	
	max	°C	+70	
Resistance & Protection				
Frontal IP degree			IP65	
Terminals IP degree			IP20	


## **Dimensions**





Series	L			
	1	2	3.	8
GX16	54	62.5	71	113.4
GX20	54	62.5	71	113.4

## Wiring diagrams



## Certifications and compliance

Compliance

CSA C22.2 n° 14

IEC/EN/BS 60947-1

IEC/EN/BS 60947-3

IEC/EN/BS 60947-5-1

IEC/EN/BS 61058-1

UL60947-4-1

Certificates

cULus

EAC

ETIM classification

**ETIM 8.0** 

EC001029 -Selector switch, complete